

**MAXIMUM  
CONVENIENCE**



# ChargeMate™

**Deka ChargeMate** combines a battery and charger into one unit to eliminate the need for remote charging equipment. Just connect the battery to its own internal charger, and plug it into any 15 amp 120 volt AC outlet for safe, easy charging anywhere, at any time...for maximum convenience and flexibility.

Only **ChargeMate** features a **Deka** precision-constructed industrial battery, built with the world's most advanced computer-integrated manufacturing methods for the highest quality and best performance anywhere.

The specially matched auto start/stop charger gives the **Deka ChargeMate** maximum power, longer life and ease of operation.

Available in 12- and 24-volt, 150-425 ampere hour, the **Deka ChargeMate** fits all major sizes of pallet jacks.



QUALITY SYSTEM  
CERTIFIED  
**ISO 9001**  
**ISO/TS 16949**  
ENVIRONMENTAL  
SYSTEM CERTIFIED  
**ISO 14001**

#### RECHARGE GUIDE:

ESTIMATED HOURS OF OPERATION	APPROX. HOURS TO RECHARGE
1	1.25 – 1.30
2	2.50 – 3.00
3	4.00 – 4.30
4	4.00 – 4.75
5	5.45 – 7.30
6	7.30 – 8.15

#### SPECIFICATIONS\*:

LAYOUT NUMBER	BATTERY TYPE	A.H. CAPACITY 6 HR. RATE	K.W.H. CAP. 6 HR. RATE	A.C. SUPPLY	DIMENSIONS (INCHES)			APPROX. WEIGHT (lbs.)
					LENGTH	WIDTH	HEIGHT	
IST1061	6-D75-11	375	4.37	120 Volts	31¼	7¾	23¾	505
IST1061	6-D85-11	425	4.94	120 Volts	31¼	7¾	23¾	526
IST3167	12-D75-5	150	3.50	120 Volts	24¼	8⅞	23¼	450
IST3167	12-D85-5	170	3.95	120 Volts	24¼	8⅞	23¼	470
IST3416	12-D75-5	150	3.50	120 Volts	33⅞	6⅞	23¼	450
IST3416	12-D85-5	170	3.95	120 Volts	33⅞	6⅞	23¼	470
IST3415	12-D75-7	225	5.24	120 Volts	30½	8⅞	23¼	581
IST3415	12-D85-7	255	5.92	120 Volts	30½	8⅞	23¼	607
IST3163	12-D75-11	375	8.74	120 Volts	31¾	12⅞	23¼	925
IST3163	12-D85-11	425	9.88	120 Volts	31¾	12⅞	23¼	958

\* Additional models are available upon request. Contact factory for specifications and pricing.

**"POWERED FOR PERFORMANCE"®**

DISTRIBUTED BY:

**EAST PENN manufacturing co., inc.**

Lyon Station, PA 19536-0147 • Phone: 610-682-6361 • Fax: 610-682-4212

Order Department Hotline: 610-682-3260

www.dekabatteries.com • e-mail: epmmotve@eastpenn-deka.com

E.P.M. Form No. 0623 Rev. 3/10  
© 2010 by EPM Printed in U.S.A.

All data subject to change without notice.  
No part of this document may be copied or reproduced, electronically or mechanically, without written permission from the company.